



Description


IP66. Class I. Class II on request. IK08. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Optional 2200 K version up to max. 1050mA available. To be specified at time of ordering.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept.

Luminaire can be mounted for up or down lighting.

Weight	1.90 kg
Light distribution	symmetric, narrow beam [E]
Light source	LED-3/13W / 1400 mA - 3000 K
CRI	80
Power supply	EC
BUG	B2 U0 G0
LEDs	3
Rated input power	14 W
Nominal Lumen (lm)	
LED Lumen	550
Total Lumen	1650
Tj	85
Rated lumens (lm)	
LED Lumen	441
Total Lumen	1322.9
Та	25







Specifications Material description

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours

RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

RAL7016 Anthracite grey

RAL/016 Anthracite gre

Gasket Silicone CCG® Controlled Compression Gasket
Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK08
Corrosion resistance 5CE

Electrical description

Power supply 220-240V / 50-60 Hz

Driver / Ballast Standard. Optional DALI version available. To be specified at time of ordering.

Power factor > 0.9 Surge protection 1/2 kV

Fagerhult Lighting Ltd

131-9976





Additional information

Lifetime

Ta=25° L90B10 > 90000h






Optical Accessories

Colour correction filter

Description	Part ID
IF-3000K > 2400K	131-9556

Honeycomb louvre

Description	Part ID	
IW-RLS410	131-9555	



RLS410 LED



Control

DALI interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	l