### **STO134 LED Stainless Steel**






IP66, Class I. Class II on request. IK07. Marine-grade, diecast aluminium alloy with polished stainless steel frame. 5CE superior corrosion protection including PCS hardware. Silicone rubber gasket. Polycarbonate main lens. Two cable entries.


Pre-installation blockout is recommended for mounting in concrete, available on request.

Weight	1.20 kg
Light distribution	diffused distribution
Light source	LED-5W / 250 mA - 2700 K
CRI	80
Power supply	EC
LEDs	1
Rated input power	5.6 W
Rated lumens (lm)	
LED Lumen	75.4
Total Lumen	75.4
Та	25
Nominal Lumen (lm)	
LED Lumen	720
Total Lumen	720
Tc	25

# we-ef

#### **STO134 LED Stainless Steel**





# **Specifications**

## **Material description**

Body Marine-grade die-cast aluminium alloy

Lens Polycarbonate

Colours Stainless Steel

Gasket Silicone rubber gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK07
Corrosion resistance 5CE

### **Electrical description**

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter

Power factor > 0.9Surge protection 1-2/2 kV

#### **Additional information**

Lifetime Ta=25° L80B10 > 54000h

Energy efficiency class C-D (Light source)

#### **Fagerhult Lighting Ltd**




### **STO134 LED Stainless Steel**


## **Mounting Accessories**

## **Installation blockout**

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	Н3	Weight (kg)
Installation blockout BST13-I	190-9030	130	12	270	338		65	107		0.90



Installation blockout BST13-II 190-9031 145 22 270 280 338 65 75 107 0.90



## 190-9039

## **STO134 LED Stainless Steel**



## **Control**

### **DALI** interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	