#### STL134 LED





#### **Description**

IP66, Class I. Class II on request. IK07. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection including PCS hardware. Polycarbonate main lens. Silicone rubber gasket. Luminaire is factory-sealed and does not need to be opened during installation.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. Two cable entries.


Pre-installation blockout is recommended for mounting in concrete, available on request.

Weight	0.90 kg
Light distribution	Shielded
Light source	LED-6W / 350 mA - 3000 K
CRI	80
Power supply	EC
LEDs	1
Rated input power	8 W
Rated lumens (lm)	
LED Lumen	25.2
Total Lumen	25.2
Та	25
Nominal Lumen (lm)	
LED Lumen	1050
Total Lumen	1050
Тс	25

#### STL134 LED







# **Specifications Material description**

Body Marine-grade die-cast aluminium alloy

Lens Polycarbonate

Colours RAL9004 Signal black

RAL9006 White aluminium

RAL9007 Grey aluminium

RAL7016 Anthracite grey

RAL9016 Traffic white

Gasket Silicone rubber gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK07
Corrosion resistance 5CE

### **Electrical description**

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter

Power factor > 0.9 Surge protection 1-2/2 kV

#### **WE-EF LEUCHTEN GmbH**

# 190-9005

#### STL134 LED



#### **Additional information**

Lifetime Ta=25° L80B10 > 54000h

Energy efficiency class C (Light source)


#### STL134 LED




# **Mounting Accessories**

# **Installation blockout**

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	Н3	Weight (kg)
Installation blockout BST13-I	190-9030	130	12	270	338		65	107		0.90



Installation blockout BST13-II 190-9031 145 22 270 280 338 65 75 107 0.90



# 190-9005

#### STL134 LED



# **Control**

# **DALI** interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	g