





#### **Description**

LED upgrade kit to repair or upgrade installed RFL530-SE LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire. Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current RFL530-SE LED luminaires

### **RFL530-SE LED Upgrade Kit**



#### Pole mounted

# **Specifications Material description**

Body Chassis made of coated steel

Lens NA

Colours RAL9006 White aluminium

Gasket NA

Fasteners Polycarbonate holder

Corrosion resistance 5CE +Primer

#### **Electrical description**

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter. DALI

Power factor > 0.9

#### **Additional information**

Lifetime  $Ta=25^{\circ} L90B10 > 90000h$ 

Energy efficiency class C-D (Light source)

## **RFL530-SE LED Upgrade Kit**



Pole mounted

Options
Light distribution

**Colour temperature Nominal Watt** 

0 W

[S60] [S65] [S70] or [R65]

2700-4000K

## **RFL530-SE LED Upgrade Kit**



#### **Pole mounted**

## Configurations

Light distribution	Part ID	Light source	Rated lumens	Rated input power	CRI	Weight (kg)
[S60][S65][S70] or [R65]	111-1234	Chassis Kit LED-12/24W / 700mA			70/80	1.20
	111-1254	Chassis Kit LED-12/12W / 350mA			70/80	1.20
	111-1257	Chassis Kit LED-24/24W / 350mA			70/80	1.20
	111-1259	Chassis Kit LED-24/48W / 700mA			70/80	1.20
	111-1260	Chassis Kit LED-24/72W / 1050mA			70/80	1.20