


#### Wall luminaires recessed



Description

IP66, Class I. IK07. Marine-grade, die-cast aluminium alloy with polished stainless steel frame. 5CE superior corrosion protection including PCS hardware. Silicone rubber gasket. Polycarbonate main lens. Two cable entries.

Pre-installation blockout is recommended for mounting in concrete, available on request.



#### WE-EF LIGHTING Pty Ltd



#### Wall luminaires recessed

## **Specifications**

#### **Material description**

Body Marine-grade, die-cast aluminium alloy

Lens Polycarbonate

Colours Stainless Steel

Gasket Silicone rubber gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware (unpainted)

Ingress protection IP66
Impact resistance IK07

Corrosion resistance 5CE. 5CE+Primer optional

#### **Electrical description**

Power supply 230V / 50 Hz

Driver / Ballast Integral EC electronic converter

#### **Additional information**

Lifetime  $Ta=40^{\circ} L80B10 > 54000h$ 

Warranty The product is supplied with 10-year warranty. Please refer to the LED Warranty Statement

located on www.we-ef.com for further details.



#### Wall luminaires recessed

# Options Light distribution

**Colour temperature Nominal Watt** 

diffused distribution



2700 K

0 W



#### Wall luminaires recessed

# **Configurations**

Light distribution	Part ID	Light source	Rated lumens	Rated input power	CRI	Weight (kg)
diffused distribution +	190-9039	LED-5W / 250 mA - 2700 K	75.4	5.6 W	80	1.20



#### Wall luminaires recessed

#### **Control**

### 1-10 V analogue dimming interface

Description	Part ID	С	
1-10 V analogue dimming interface	430-0011	90	



#### Wall luminaires recessed

#### **DALI** interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined	
		-Separate addressing & grouping from control gear  Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	g




#### Wall luminaires recessed

# **Mounting Accessories**

#### **Installation blockout**

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	Н3	Weight (kg)
Installation blockout BST13-I	190-9030	130	12	270	338		65	107		0.90



Installation blockout BST13-II 190-9031 145 22 270 280 338 65 75 107 0.90

