#### **OLV344 LED**

# we-ef



Weight

#### Description

IP65, Class I. IK07. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection + primer including PCS hardware. Silicone CCG® Controlled Compression Gasket. Safety glass lens. Two cable entries. Integral EC electronic converter. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept. Factory installed LED circuit board. 1-10V or DALI interface on request. Optional 2200 K version available. To be specified at time of ordering.

Can be mounted up or down.


- veignt	11:10 kg
Light distribution	asymmetric, side throw [S70]
Light source	LED-24/24W / 350 mA - 2700 K
CRI	80
Power supply	EC
LEDs	24
Rated input power	26.5 W
Nominal Lumen (lm)	
LED Lumen	145
Total Lumen	3480
Tj	85
Rated lumens (lm)	
LED Lumen	120.8
Total Lumen	2898.6
Та	25


11.40 kg


#### 132-0647

#### **OLV344 LED**









# **Specifications Material description**

Body Marine-grade die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware (unpainted)

Ingress protection IP65
Impact resistance IK07

Corrosion resistance 5CE+Primer

## **Electrical description**

Power supply 230V / 50 Hz

Driver / Ballast Integral EC electronic converter

#### **Additional information**

Lifetime	$T_a=40^{\circ} L90B10 > 90000h$
Warranty	The product is supplied with 10-year warranty. Please refer to the LED Warranty Statement
	located on www.we-ef.com for further details.

#### **WE-EF LIGHTING Pty Ltd**

# 132-0647

#### **OLV344 LED**



### **Control**

# 1-10 V analogue dimming interface

ription Part ID	С
V analogue dimming interface 430-0011	90

# 132-0647

#### **OLV344 LED**



#### **DALI** interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressin and the command scope has changed!	ng