RLS410 LED





Description

IP66. Class I. IK08. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Optional 2200 K version up to max. 1050mA available. To be specified at time of ordering.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept.


Luminaire can be mounted for up or down lighting.

Weight 1.90 kg Light distribution rectangular, side throw [R45] Light source LED-3/13W / 1400 mA - 2700 K CRI 80 Power supply EC				
Light source LED-3/13W / 1400 mA - 2700 K CRI 80				
CRI 80				
Power supply EC				
BUG B0 U0 G0				
LEDs 3				
Rated input power 14 W				
Nominal Lumen (Im)				
LED Lumen 520				
Total Lumen 1560				
Tj 85				
Rated lumens (lm)				
LED Lumen 310.4				
Total Lumen 931.3				
Ta 25				

RLS410 LED







Specifications Material description

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK08

Corrosion resistance 5CE+Primer

Electrical description

Driver / Ballast Integral EC electronic converter

Additional information

Lifetime Ta=40° L90B10 > 90000h

WE-EF LIGHTING Pty Ltd

131-9603

RLS410 LED



Control

1-10 V analogue dimming interface

Description	Part ID	С
1-10 V analogue dimming interface		90

131-9603

RLS410 LED



DALI interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	ng

131-9603

RLS410 LED



Optical Accessories

Colour correction filter

Description	Part ID
IF-3000K > 2400K	131-9556

Honeycomb louvre

Description	Part ID	
Honeycomb louvre IW	131-9555	

