RLS410 LED





Description

IP66. Class I. IK08. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Optional 2200 K version up to max. 1050mA available. To be specified at time of ordering.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept.


Luminaire can be mounted for up or down lighting.

| Weight | 1.90 kg |
|--------------------|------------------------------|
| Light distribution | symmetric, narrow beam [E] |
| Light source | LED-3/13W / 1400 mA - 3000 K |
| CRI | 80 |
| Power supply | EC |
| BUG | B2 U0 G0 |
| LEDs | 3 |
| Rated input power | 14 W |
| Nominal Lumen (lm) | |
| LED Lumen | 550 |
| Total Lumen | 1650 |
| Tj | 85 |
| Rated lumens (lm) | |
| LED Lumen | 441 |
| Total Lumen | 1322.9 |
| Та | 25 |

RLS410 LED







Specifications Material description

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket
Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK08

Corrosion resistance 5CE+Primer

Electrical description

Driver / Ballast Integral EC electronic converter

Additional information

Lifetime Ta=40° L90B10 > 90000h

131-9976

RLS410 LED



Control

1-10 V analogue dimming interface

| Description Part ID | С |
|--|----|
| 10 V analogue dimming interface 430-00 | 90 |

131-9976

RLS410 LED



DALI interface

| Description | Part ID | Additional information | С |
|----------------|----------|---|----|
| DALI interface | 430-0013 | DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0). | 90 |
| | | Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear | |
| | | Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressin and the command scope has changed! | ıg |

131-9976

RLS410 LED



Optical Accessories

Colour correction filter

| Description | Part ID |
|------------------|----------|
| IF-3000K > 2400K | 131-9556 |

Honeycomb louvre

| Description | Part ID | |
|---------------------|----------|--|
| Honeycomb louvre IW | 131-9555 | |

