RLS420 LED





Description

IP66. Class I. IK08. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Optional 2200 K version up to max. 1050mA available. To be specified at time of ordering.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept.


Luminaire can be mounted for up or down lighting.

Weight	2.60 kg		
Light distribution	symmetric, narrow beam [E]		
Light source	LED-6/12W / 700 mA - 3000 K		
CRI	80		
Power supply	EC		
BUG	B1 U0 G0		
LEDs	6		
Rated input power	14.5 W		
Nominal Lumen (lm)			
LED Lumen	290		
Total Lumen	1740		
Tj	85		
Rated lumens (lm)			
LED Lumen	219		
Total Lumen	1313.8		
Та	25		

RLS420 LED







Specifications Material description

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket
Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK08

Corrosion resistance 5CE+Primer

Electrical description

Driver / Ballast Standard. Optional DALI version available. To be specified at time of ordering.

Additional information

Lifetime Ta=40° L90B10 > 90000h

131-9992

RLS420 LED



Control

1-10 V analogue dimming interface

Part II	С
-10 V analogue dimming interface 430-0	90

131-9992

RLS420 LED



DALI interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressin and the command scope has changed!	ng

131-9992

RLS420 LED



Optical Accessories

Colour correction filter

Description	Part ID
IF-3000K > 2400K	131-9707

Honeycomb louvre

Description	Part ID	
Honeycomb louvre IW	131-9706	

