


Description


IP66, Class I. Class II on request. IK07. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection including PCS hardware. Polycarbonate main lens. Silicone rubber gasket. Luminaire is factory-sealed and does not need to be opened during installation.

Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. Two cable entries.

Pre-installation blockout is recommended for mounting in concrete, available on request.

Weight	0.90 kg
Light distribution	Shielded
Light source	LED-6W / 350 mA - 2700 K
CRI	80
Power supply	EC
LEDs	1
Rated input power	8 W
Rated lumens (lm)	
LED Lumen	23.8
Total Lumen	23.8
Та	25
Nominal Lumen (lm)	
LED Lumen	990
Total Lumen	990
Тс	25





Specifications Material description

Body	Marine-grade die-cast aluminium alloy						
Lens	Polycarbonate						
Colours	RAL9004 Signal black						
	RAL9006 White aluminium						
	RAL9007 Grey aluminium						
	RAL7016 Anthracite grey						
	RAL9016 Traffic white						
Gasket	Silicone rubber gasket						
Fasteners	PCS Polymer Coated Stainless Steel Hardware						
Ingress protection	IP66						
Impact resistance	IK07						
Corrosion resistance	5CE						

Electrical description

Power supply	220-240V / 50-60 Hz
Driver / Ballast	Integral EC electronic converter
Power factor	> 0.9
Surge protection	1-2/2 kV

190-9036

STL134 LED



Additional information

Lifetime	Ta=25° L80B10 > 54000h
Energy efficiency class	C (Light source)

190-9036

STL134 LED

Mounting Accessories

Installation blockout

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	H3	Weight (kg)
Installation blockout BST13-I	190-9030 [130 		270	338		65	107		0.90
				1 H2						
Installation blockout BST13-II	190-9031		22	270	280	338	65	75	107	0.90
				12 H3						

we-ef

190-9036

STL134 LED

Control

DALI interface

Description	Part ID	Additional information					
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90				
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear					
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!					