#### MRY224 LED - 1000 mm





#### **Description**

IP66. Class I. IK10. Marine-grade, all-aluminium construction. Pole section features anodised aluminium core. 5CE superior corrosion protection + primer including PCS hardware. Polycarbonate main lens, UV-stabilised. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control.


Available in 2200 K on request

Weight	12.40 kg		
Light distribution	symmetric [C70]		
Light source	LED-11W / 300 mA - 3000 K		
CRI	80		
Power supply	EC		
LEDs	1		
Rated input power	13.5 W		
Rated lumens (lm)			
LED Lumen	890.7		
Total Lumen	890.7		
Та	25		
Nominal Lumen (lm)			
LED Lumen	1395		
Total Lumen	1395		
Тс	25		

#### MRY224 LED - 1000 mm







# **Specifications Material description**

Body Marine-grade, all-aluminium construction. Pole section features anodised aluminium core

Lens Polycarbonate, UV-stabilised

Colours RAL9004 Signal black

RAL9006 White aluminium

RAL9007 Grey aluminium

RAL9016 Traffic white

Gasket Silicone CCG® Controlled Compression Gasket

Fasteners PCS hardware

Ingress protection IP66
Impact resistance IK10

Corrosion resistance 5CE+Primer

## **Electrical description**

Driver / Ballast Integral EC electronic converter

Power factor > 9.0 Surge protection 10/10kV

#### **Additional information**

Lifetime	11W - Ta=25 <sup>o</sup> L70B50>50000h	
	15W - Ta=25° L70B50>50000h	

#### **WE-EF LIGHTING Pty Ltd**

#### MRY224 LED - 1000 mm



## **Control**

# 1-10 V analogue dimming interface

Description	Part ID C
1-10 V analogue dimming interface	430-0011 9

#### MRY224 LED - 1000 mm



#### **DALI** interface

Description	Part ID	Additional information	С
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear	
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!	g

#### MRY224 LED - 1000 mm



# **Mounting Accessories**

## **Planted root**

Description	Part ID	D1	D2	D3	D4	H1	H2	Weight (kg)
Planted root ESZ4	300-9090	55	45	70	100	400	350	3.50

