### **FLC301 Space frame**





#### **Description**

IP66. IK07. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation.

Integral EC electronic converter in thermally-separated compartment. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control.


Including terminal box, for mounting on ø 48-60 mm pipes or space frames.


Mains voltage versions only, ON-OFF Class I or DALI interface available on request (converter in thermally-separated compartment); refer to accessory listings.

Weight	1.70 kg		
Light distribution	symmetric, narrow beam [E]		
Light source	LED-1/4W / 350 mA - 3000 K		
CRI	80		
Power supply	EC		
LEDs	1		
Rated input power	5 W		
Nominal Lumen (lm)			
LED Lumen	490		
Total Lumen	490		
Tj	85		
Rated lumens (lm)			
LED Lumen	415.2		
Total Lumen	415.2		
Та	25		

# we-ef

### **FLC301 Space frame**





# **Specifications Material description**

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware (unpainted)

Ingress protection IP66
Impact resistance IK07

Corrosion resistance 5CE+Primer

### **Electrical description**

Driver / Ballast Integral EC electronic converter in thermally-separated compartment

#### Additional information

Lifetime Ta=25° L90B10 > 90000h

# **FLC301 Space frame**



### **Control**

### 1-10 V analogue dimming interface

Description	Part ID	С
1-10 V analogue dimming interface	430-0011	90

### **DALI** interface

Description	Part ID	Additional information
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).
		Dali 2.0
		-Application controllers and Input devices defined
		-Single-masters and multi-masters allowed
		-Event priorities defined
		-Separate addressing & grouping from control gear
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!




# we-ef

# **Optical Accessories**

### **Linear spread lens**

Description	Part ID	C1	
Linear spread lens IO-180	145-7229	42.5	



### Wallwash lens

Description Par	C1
Vallwash lens IO-20 14	42.5






### **FLC301 Space frame**


### **Honeycomb louvre**

Description	Part ID	C1
Honeycomb louvre IW	145-7231	42.5



### Glare shield

Description	ID A	C1
Glare shield ES	7232 20.5	58





# **FLC301 Space frame**

#### **Snoot**

Description	Part ID	Α	C1
Snoot ET	145-7233	22.5	58

