

RFL530-SE LED Upgrade Kit



Description

LED upgrade kit to repair or upgrade installed RFL530-SE LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current RFL530-SE LED luminaires

Weight	1.20 kg
Light distribution	[S60] [S65] [S70] or [R65]
Light source	Chassis Kit LED-12/24W / 700mA
CRI	70/80



Specifications

Material description

Body	Chassis made of coated steel
Lens	NA
Colours	<div></div> RAL9006 White aluminium
Gasket	NA
Fasteners	Polycarbonate holder
Corrosion resistance	5CE +Primer

Electrical description

Driver / Ballast	Integral EC electronic converter. DALI
Power factor	> 0.9

Additional information

Lifetime	Ta=40° L90B10 > 90000h
----------	------------------------