# 146-0515+146-0418 FLC131 LED - Wall bracket




#### Description


IP66, Class I. IK07. Marine-grade, all-aluminium construction. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Integral EC electronic converter in thermally-separated compartment. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept. Two cable entries.

Knuckle permits 350° horizontal and 180° vertical aiming of optics.

Weight	4.50 kg
Light distribution	linear spread, very narrow beam [EE]
Light source	LED-12/24W / 700 mA - 3000 K
CRI	80
Power supply	EC
LEDs	12
Rated input power	27 W
Nominal Lumen (lm)	
LED Lumen	290
Total Lumen	3480
Тј	85
Rated lumens (lm)	
LED Lumen	228.7
Total Lumen	2744.2
Та	25

# 146-0515+146-0418 FLC131 LED - Wall bracket





### Specifications Material description

Body	Marine-grade, die-cast aluminium alloy
Lens	Safety glass lens
Colours	RAL9004 Signal black
	RAL9006 White aluminium
	RAL9007 Grey aluminium
Gasket	Silicone CCG <sup>®</sup> Controlled Compression Gasket
Fasteners	PCS Polymer Coated Stainless Steel Hardware (unpainted)
Ingress protection	IP66
Impact resistance	IK07
Corrosion resistance	5CE+Primer

#### **Electrical description**

Power supply	230V / 50 Hz
Driver / Ballast	Integral EC electronic converter in thermally-separated compartment

#### **Additional information**


Lifetime	Ta=40° L90B10 > 90000h
Warranty	The product is supplied with 10-year warranty. Please refer to the LED Warranty Statement located on www.we-ef.com for further details.

FLC131 LED - Wall bracket

## **Optical Accessories**


#### Glare shield

Description
e shield ES



#### Snoot

Description	Part ID A	C1
Snoot ET	146-0397 95,5	126



we-ef

#### FLC131 LED - Wall bracket




#### Surface wash lens

Description	Part ID	C1
10-360	146-0419	110



#### Linear louvre

scription Part ID	C1
ear louvre IL 146-9055	110



#### FLC131 LED - Wall bracket




#### Linear spread lens

Description	n Part ID	C1
10-180-FLC131-LED	C131-LED 146-0418	110



### Wallwash lens

Description	Part ID	C1
IO-20-WW-FLC131-LED	185-7029	110




#### FLC131 LED - Wall bracket



#### Honeycomb louvre

W-FLC131-LED 146-0625 110	Description	Part ID	C1		
	IW-FLC131-LED	146-0625	110		



### FLC131 LED - Wall bracket

# Control

### DALI interface

Description	Part ID	Additional information
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).
		Dali 2.0
		-Application controllers and Input devices defined
		-Single-masters and multi-masters allowed
		-Event priorities defined
		-Separate addressing & grouping from control gear
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed!