FLC141 LED - Wall bracket





Description

IP66, Class I. IK07. Marine-grade, all-aluminium construction. 5CE superior corrosion protection + primer including PCS hardware. Safety glass lens. Silicone CCG® Controlled Compression Gasket. Luminaire is factory-sealed and does not need to be opened during installation. Integral EC electronic converter in thermally-separated compartment. Advanced thermal management protects LEDs while optimising lumens output. CAD-optimised optics for superior illumination and glare control. OLC® One LED Concept. Two cable entries.


Knuckle permits 350° horizontal and 180° vertical aiming of optics.


2700 K option available on request.


| Weight | 5.80 kg | | | |
|--------------------|------------------------------|--|--|--|
| Light distribution | symmetric, wide beam [B] | | | |
| Light source | LED-24/48W / 700 mA - 4000 K | | | |
| CRI | 80 | | | |
| Power supply | EC | | | |
| LEDs | 24 | | | |
| Rated input power | 54 W | | | |
| Nominal Lumen (lm) | | | | |
| LED Lumen | 310 | | | |
| Total Lumen | 7440 | | | |
| Tj | 85 | | | |
| Rated lumens (lm) | | | | |
| LED Lumen | 240 | | | |
| Total Lumen | 5760.1 | | | |
| Та | 25 | | | |

FLC141 LED - Wall bracket









Specifications Material description

Body Marine-grade, die-cast aluminium alloy

Lens Safety glass lens

Colours RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

Gasket Silicone CCG® Controlled Compression Gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware (unpainted)

Ingress protection IP66
Impact resistance IK07

Corrosion resistance 5CE+Primer

Electrical description

Power supply 230V / 50 Hz

Driver / Ballast Integral EC electronic converter in thermally-separated compartment

Additional information

Lifetime Ta=40° L90B10 > 90000h

Warranty The product is supplied with 10-year warranty. Please refer to the LED Warranty Statement located on www.we-ef.com for further details.


FLC141 LED - Wall bracket



Optical Accessories


Glare shield

| Description | Part ID A | C1 |
|-----------------|------------|--------|
| Glare shield ES | 146-0229 1 | 20 145 |



Snoot

| Description | Part ID A | C1 |
|-------------|--------------|-----|
| Snoot ET | 146-0398 120 | 145 |





we-ef


Linear spread lens

| Description | Part ID | C1 | |
|-------------------|----------|-----|--|
| IO-180-FLC141-LED | 146-0439 | 145 | |



Surface wash lens

| escription Part ID | C1 |
|--------------------------|-----|
| -360-FLC141-LED 146-9950 | 145 |







we-ef


Wallwash lens

| Description | Part ID | C1 |
|---------------------|----------|-----|
| IO-20-WW-FLC141-LED | 146-0646 | 145 |



Linear louvre








Honeycomb louvre

| Description | Part ID | C1 |
|---------------|----------|-----|
| IW-FLC141-LED | 146-0626 | 145 |



FLC141 LED - Wall bracket



Control

DALI interface

| Description | Part ID | Additional information |
|-------------------------|--|---|
| DALI interface 430-0013 | DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0). | |
| | | Dali 2.0 |
| | | -Application controllers and Input devices defined |
| | | -Single-masters and multi-masters allowed |
| | | -Event priorities defined |
| | | -Separate addressing & grouping from control gear |
| | | Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing and the command scope has changed! |