#### ETC119 LED





#### **Description**

IP67. Class III. IK09. Stainless steel construction including PCS hardware. Silicone rubber gasket. Safety glass lens. Luminaire can be driven over at low speed. Factory-sealed termination chamber complete with cable gland and 1.5 m of flexible PVC free cable. IP68 in-line connector facilitates easy removal for off-site lamp replacement. Factory installed LED circuit board. LED boards can be easily removed for upgrading.


Luminaire requires installation blockout. To be ordered separately.


The luminaire is not suitable for permanent underwater operation.

Weight	1.00 kg
Light distribution	symmetric, diffused distribution
Light source	LED-1/1W - 4000 K
CRI	75
LEDs	1
Rated input power	1 W
Nominal Lumen (lm)	
LED Lumen	170
Total Lumen	170
Тј	85
Rated lumens (lm)	
LED Lumen	50.4
Total Lumen	50.4
Та	25

#### ETC119 LED







# **Specifications**

# **Material description**

Body Stainless steel construcion

Lens Safety glass lens; max. load 5 tonnes

Colours Stainless Steel

Gasket Silicone rubber gasket

Fasteners PCS polymer coated stainless steel

Ingress protection IP67
Impact resistance IK09

#### **Electrical description**

Driver / Ballast Electronic converter required. To be ordered separately.

Surge protection 1/2 kV (optional SP10)

#### **Additional information**

Lifetime Ta=25° L90B10 > 90000h

Energy efficiency class E (Light source)


### **ETC119 LED**




# **Mounting Accessories**

## **Installation blockout**

Description	Part ID	D1	D2	H1	Weight (kg)	D	Н
Blockout, Plastic (shallow)	185-0412	95	240	110	0.50	95/240	110



Blockout, Plastic (deep) 185-0797 95 170 220 0.50 95/170 220



## **ETC119 LED**



### **Installation cover**

Description	Part ID	C1
Installation cover BE	185-0414	95



—C1—


## **ETC119 LED**




# **Electrical Accessories**

### **Transformers**

Description	Part ID	Α	В	C1	С
Transformer AC 12 V/300 W	185-1550	185	105	90	105




Transformer AC 12 V/20 W 185-1796 140 65 90 90




## **ETC119 LED**



Description	Part ID	Α	В	C1	С
Transformer AC 12 V/100 W	185-1797	170	80	90	100




Transformer TVM-AC 24 V/20W 185-2884 140 65 90



## **ETC119 LED**




Description	Part ID	А	В	C1
Transformer TVM-AC 24 V/50W	185-2885	140	65	90



# **Sealable junction box**

Description	Part ID	C1	M1	M2
Sealable junction box SJB130	185-1624	146	Ø 10	Ø 12 - 19




## **ETC119 LED**



#### **Main converter**

Description	Part ID	Α	В	C1
Main converter TVE-DC 24 V/12 W	400-0310	90	61	18



Main converter TVE-DC 24 V/60 W 400-0311 89 59 72

