
#### STO134 LED Stainless Steel

we-ef



#### Description

IP66, Class I. Class II on request. IK07. Marine-grade, diecast aluminium alloy with polished stainless steel frame. 5CE superior corrosion protection including PCS hardware. Silicone rubber gasket. Polycarbonate main lens. Two cable entries.


Pre-installation blockout is recommended for mounting in concrete, available on request.


Weight	1.20 kg
Light distribution	diffused distribution
Light source	LED-5W / 250 mA - 3000 K
CRI	80
Power supply	EC
LEDs	1
Rated input power	5.6 W
Rated lumens (lm)	
LED Lumen	78.6
Total Lumen	78.6
Та	25
Nominal Lumen (lm)	
LED Lumen	750
Total Lumen	750
Тс	25

#### 190-9014

# we-ef

#### STO134 LED Stainless Steel





## Specifications Material description

Body	Marine-grade die-cast aluminium alloy
Lens	Polycarbonate
Colours	Stainless Steel
Gasket	Silicone rubber gasket
Fasteners	PCS Polymer Coated Stainless Steel Hardware
Ingress protection	IP66
Impact resistance	IK07
Corrosion resistance	5CE

#### **Electrical description**

Power supply	220-240V / 50-60 Hz
Driver / Ballast	Integral EC electronic converter
Power factor	> 0.9
Surge protection	1-2/2 kV

#### Additional information

Lifetime	Ta=25° L80B10 > 54000h
Energy efficiency class	C-D (Light source)

## 190-9014

## STO134 LED Stainless Steel

## **Mounting Accessories**

#### Installation blockout

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	H3	Weight (kg)
Installation blockout BST13-I	190-9030 	130 −c1— C	12 2 	270	338		65	107		0.90
				1 H2						
				1 D2						
Installation blockout BST13-II	190-9031	145	22	270	280	338	65	75	107	0.90
		C2								
			HI F	H2 H3						
			D1 [	D2 D3						

we-ef

## 190-9014

## STO134 LED Stainless Steel

## Control

## **DALI** interface

Description	Part ID	Additional information				
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).	90			
		Dali 2.0 -Application controllers and Input devices defined -Single-masters and multi-masters allowed -Event priorities defined -Separate addressing & grouping from control gear				
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressi and the command scope has changed!	ng			