



Description


IP66, Class I. Class II on request. IK07. Marine-grade, die-cast aluminium alloy. 5CE superior corrosion protection including PCS hardware. Polycarbonate main lens. Silicone rubber gasket. Luminaire is factory-sealed and does not need to be opened during installation.


Integral EC electronic converter. Advanced thermal management protects LEDs while optimising lumens output. Two cable entries.

Pre-installation blockout is recommended for mounting in concrete, available on request.

Weight	0.90 kg
Light distribution	Shielded
Light source	LED-6W / 350 mA - 4000 K
CRI	80
Power supply	EC
LEDs	1
Rated input power	8 W
Rated lumens (lm)	
LED Lumen	26.6
Total Lumen	26.6
Та	25
Nominal Lumen (lm)	
LED Lumen	1110
Total Lumen	1110
Тс	25







Specifications Material description

Body Marine-grade die-cast aluminium alloy

Lens Polycarbonate

Colours

RAL9004 Signal black

RAL9006 White aluminium
RAL9007 Grey aluminium

RAL7016 Anthracite grey

RAL9016 Traffic white

Gasket Silicone rubber gasket

Fasteners PCS Polymer Coated Stainless Steel Hardware

Ingress protection IP66
Impact resistance IK07
Corrosion resistance 5CE

Electrical description

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter

Power factor > 0.9 Surge protection 1-2/2 kV

Fagerhult Lighting Ltd

190-9006





Additional information

Lifetime Ta=25° L80B10 > 54000h


Energy efficiency class C (Light source)



Mounting Accessories

Installation blockout

Description	Part ID	C1	C2	D1	D2	D3	H1	H2	Н3	Weight (kg)
Installation blockout BST13-I	190-9030	130	12	270	338		65	107		0.90



Installation blockout BST13-II

190-9031


145 22 270 280

338

65

75

107 0.90





Control

DALI interface

Description	Part ID	Additional information	С				
DALI interface	430-0013	DALI variant. The luminaire is equipped with a DT6 Dali driver (Dali 2.0).					
		Dali 2.0					
		-Application controllers and Input devices defined					
		-Single-masters and multi-masters allowed					
		-Event priorities defined					
		-Separate addressing & grouping from control gear					
		Note: Mixing Dali 1 and Dali 2.0 drivers can cause problems because the addressing)				
		and the command scope has changed!					