



### Description

LED upgrade kit to repair or upgrade installed VFL530-SE LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire. Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current VFL530-SE LED luminaires.

## Pole mounted

---

### Specifications

#### Material description

---

Body	Chassis made of coated steel
Lens	NA
Colours	 RAL9006 White aluminium
Gasket	NA
Fasteners	Polycarbonate holder
Corrosion resistance	NA

---

#### Electrical description

---

Driver / Ballast	Integral EC electronic converter. DALI
Power factor	> 9.0

---

#### Additional information

---

Lifetime	Ta=40° L90B10 > 90000h
----------	------------------------

---

# VFL530-SE LED Upgrade Kit

Pole mounted

---

## Options

**Light distribution**

[S60] [S65] [S70] or [R65]

**Colour temperature**

2700-4000K

**Nominal Watt**

0 W

## Pole mounted

### Configurations

Light distribution	Part ID	Light source	Rated lumens	Rated input power	CRI	Weight (kg)
[S60][S65][S70] or [R65]	108-3129	Chassis Kit LED-12/24W / 700mA			70/80	1.20
	108-3305	Chassis Kit LED-12/12W / 350mA			70/80	1.20
	108-3307	Chassis Kit LED-24/24W / 350mA			70/80	1.20
	108-3308	Chassis Kit LED-24/48W / 700mA			70/80	1.20
	108-3309	Chassis Kit LED-24/72W / 1050mA			70/80	1.20