

# RFL530-SE LED Upgrade Kit

Pole mounted

**we-ef**



## Description

LED upgrade kit to repair or upgrade installed RFL530-SE LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire. Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current RFL530-SE LED luminaires

## WE-EF LIGHTING Pty Ltd

6/13 Downard Street, 3195 Braeside, Victoria - Phone: +61 3 8587 0444 - Fax: +61 3 8587 0499

info.australia@we-ef.com - <https://we-ef.com/aus>

Subject to technical changes and errors. - Generated on 23/10/2024


# RFL530-SE LED Upgrade Kit

Pole mounted

## Specifications

### Material description

---

Body	Chassis made of coated steel
Lens	NA
Colours	 RAL9006 White aluminium
Gasket	NA
Fasteners	Polycarbonate holder
Corrosion resistance	5CE +Primer

---

### Electrical description

---

Driver / Ballast	Integral EC electronic converter. DALI
Power factor	> 0.9

---

### Additional information

---

Lifetime	Ta=40° L90B10 > 90000h
----------	------------------------

---

# RFL530-SE LED Upgrade Kit

Pole mounted

**we-ef**

## Options

**Light distribution**

[S60] [S65] [S70] or [R65]

**Colour temperature**

2700-4000K

**Nominal Watt**

0 W

**WE-EF LIGHTING Pty Ltd**

6/13 Downard Street, 3195 Braeside, Victoria - Phone: +61 3 8587 0444 - Fax: +61 3 8587 0499

info.australia@we-ef.com - <https://we-ef.com/aus>

Subject to technical changes and errors. - Generated on 23/10/2024

# RFL530-SE LED Upgrade Kit

**we-ef**

Pole mounted

## Configurations

Light distribution	Part ID	Light source	Rated lumens	Rated input power	CRI	Weight (kg)
[S60][S65][S70] or [R65]	111-1234	Chassis Kit LED-12/24W / 700mA			70/80	1.20
	111-1254	Chassis Kit LED-12/12W / 350mA			70/80	1.20
	111-1257	Chassis Kit LED-24/24W / 350mA			70/80	1.20
	111-1259	Chassis Kit LED-24/48W / 700mA			70/80	1.20
	111-1260	Chassis Kit LED-24/72W / 1050mA			70/80	1.20

### WE-EF LIGHTING Pty Ltd

6/13 Downard Street, 3195 Braeside, Victoria - Phone: +61 3 8587 0444 - Fax: +61 3 8587 0499

info.australia@we-ef.com - <https://we-ef.com/aus>

Subject to technical changes and errors. - Generated on 23/10/2024

**RFL530-SE LED Upgrade Kit**

**Pole mounted**

**WE-EF LIGHTING Pty Ltd**

6/13 Downard Street, 3195 Braeside, Victoria

Phone: +61 3 8587 0444

Fax: +61 3 8587 0499

info.australia@we-ef.com

<https://we-ef.com/aus>

Subject to technical changes and errors.

Generated on 23/10/2024