## we-ef

#### **Street and Area Lighting**





#### Description

LED upgrade kit to repair or upgrade installed RFL530-SE LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current RFL530-SE LED luminaires



#### **Street and Area Lighting**

# **Specifications Material description**

Body Chassis made of coated steel

Lens NA

Colors

Gasket NA

Fasteners Polycarbonate holder

Corrosion resistance 5CE +Primer

#### **Electrical description**

Driver / Ballast Integral EC electronic converter. DALI

Power factor > 0.9

#### **Additional information**

Lifetime Ta=25°/40° L90B10 > 90000h



**Street and Area Lighting** 

**Options** 

Light distribution Color temperature Nominal Watt



### **Street and Area Lighting**

## **Configurations**

Light distribution	Part ID	Light source	Delivered	Rated input	CRI	Weight (lb)
			lumens	power		