

Description

LED upgrade kit to repair or upgrade installed VFL520 LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire. Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.


Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current VFL520 LED luminaires.

Pole mounted

Specifications

Material description

Body	Chassis made of coated steel
Lens	NA
Colours	 RAL9006 White aluminium
Gasket	NA
Fasteners	Polycarbonate holder
Corrosion resistance	NA

Electrical description

Power supply	220-240V / 50-60 Hz
Driver / Ballast	Integral EC electronic converter. DALI
Power factor	> 9.0

Additional information

Lifetime	Ta=25° L90B10 > 90000h
Energy efficiency class	C-D (Light source)

Pole mounted

Options

Light distribution	Colour temperature	Nominal Watt
[S60] [S65] [S70] or [R65]	2700-4000K	0 W

Configurations

Light distribution	Part ID	Light source	Rated lumens	Rated input power	CRI	Weight (kg)
[S60][S65][S70] or [R65]	108-3126	Chassis Kit LED-12/24W / 700mA			70/80	1.20
	108-3298	Chassis Kit LED-12/12W / 350mA			70/80	1.20
	108-3299	Chassis Kit LED-12/36W / 1050mA			70/80	1.20