VFL520 LED Upgrade Kit





Description

LED upgrade kit to repair or upgrade installed VFL520 LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current VFL520 LED luminaires.

| Weight | 1.20 kg |
|--------------------|---------------------------------|
| Light distribution | [S60] [S65] [S70] or [R65] |
| Light source | Chassis Kit LED-12/36W / 1050mA |
| CRI | 70/80 |
| Power supply | see description |

108-3299

VFL520 LED Upgrade Kit





Specifications

Material description

Body Chassis made of coated steel

Lens NA

Colours RAL9006 White aluminium

Gasket NA

Fasteners Polycarbonate holder

Corrosion resistance NA

Electrical description

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter. DALI

Power factor > 9.0

Additional information

Lifetime $Ta=25^{\circ} L90B10 > 90000h$

Energy efficiency class C-D (Light source)