



### Description

LED upgrade kit to repair or upgrade installed VFL530 LED luminaires (from 2014) with [S60] [S65] [S70] [S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current VFL530 LED luminaires.

Weight	1.20 kg
Light distribution	[S60] [S65] [S70] or [R65]
Light source	Chassis Kit LED-12/12W / 350mA
CRI	70/80
Power supply	see description

108-3300


VFL530 LED Upgrade Kit

**we-ef**



## Specifications

### Material description

Body	Chassis made of coated steel
Lens	NA
Colours	 RAL9006 White aluminium
Gasket	NA
Fasteners	Polycarbonate holder
Corrosion resistance	NA

### Electrical description

Driver / Ballast	Integral EC electronic converter. DALI
Power factor	> 9.0

### Additional information

Lifetime	Ta=40° L90B10 > 90000h
----------	------------------------

**WE-EF LIGHTING Pty Ltd**

6/13 Downard Street, 3195 Braeside, Victoria - Phone: +61 3 8587 0444 - Fax: +61 3 8587 0499

info.australia@we-ef.com - <https://we-ef.com/aus>

Subject to technical changes and errors. - Generated on 23/10/2024

**108-3300**

**VFL530 LED Upgrade Kit**

**WE-EF LIGHTING Pty Ltd**

6/13 Downard Street, 3195 Braeside, Victoria

Phone: +61 3 8587 0444

Fax: +61 3 8587 0499

info.australia@we-ef.com

<https://we-ef.com/aus>

Subject to technical changes and errors.

Generated on 23/10/2024