





## **Description**

LED upgrade kit to repair or upgrade installed VFL530-SE LED luminaires (from 2014) with [S60][S65][S70][S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current VFL530-SE LED luminaires.

Weight	1.20 kg
Light distribution	[S60] [S65] [S70] or [R65]
Light source	Chassis Kit LED-12/24W / 700mA
CRI	70/80







## **Specifications Material description**

Body Chassis made of coated steel

Lens NA

Colours RAL9006 White aluminium

Gasket NA

Fasteners Polycarbonate holder

Corrosion resistance NA

## **Electrical description**

Power supply 220-240V / 50-60 Hz

Driver / Ballast Integral EC electronic converter. DALI

Power factor > 9.0

## Additional information

Lifetime  $Ta=25^{\circ} L90B10 > 90000h$