we-ef

RFL530-SE LED Upgrade Kit



Description

LED upgrade kit to repair or upgrade installed RFL530-SE LED luminaires (from 2014) with [S60][S65][S70][S65] light distribution.

Upgrade kit uses the latest technology for improved energy performance. Connectivity and controls dependent on previous luminaire settings; DALI and 0-10V only possible if luminaire installed with 5-wire cable. One LED retrofit kit possible per luminaire.

Upgrade Kit comes complete with driver, LED board, optics and cables. Quick installation possible with few tools. Installation only possible with 6 LED board and only for forward orientation. No rotation of lenses possible. Not available for existing hybrid installations. A backlight shield cannot be used.

Please specify wattage, colour temperature and light distribution when ordering!

For photometric data see current RFL530-SE LED luminaires

Weight	1.20 kg
Light distribution	[S60] [S65] [S70] or [R65]
Light source	Chassis Kit LED-24/72W / 1050mA
CRI	70/80

111-1260

RFL530-SE LED Upgrade Kit





Specifications

Material description

Body Chassis made of coated steel

Lens NA

Colours RAL9006 White aluminium

Gasket NA

Fasteners Polycarbonate holder

Corrosion resistance 5CE +Primer

Electrical description

Driver / Ballast Integral EC electronic converter. DALI

Power factor > 0.9

Additional information

Lifetime Ta=40° L90B10 > 90000h



111-1260 RFL530-SE LED Upgrade Kit

WE-EF LIGHTING Pty Ltd

6/13 Downard Street, 3195 Braeside, Victoria Phone: +61 3 8587 0444 Fax: +61 3 8587 0499 info.australia@we-ef.com https://we-ef.com/aus

Subject to technical changes and errors. Generated on 23/10/2024

